

# J10

## Single-Phase Extension Socket Flat Pin Installation Guide

TriCab single-phase extension sockets are designed and tested to AS/NZS 3120. They are IP66 rated, impact resistant and UV stabilized, making them suitable for most indoor and outdoor applications. Current ratings from 10 to 15 Amps.

Typical applications include:

- Commercial / Industrial
- Manufacturing
- Temporary power
- Mobile machinery and equipment

### Materials

- Lock ring, lock nut: Nylon PA66
- Transparent body: Polycarbonate PC
- Terminals: Brass

### Operating Temperature

- -40°C to 110°C
- -40°F to 230°F

### Standards

- AS/NZS 3123
- AS/NZS 60529, IEC 60529




Figure 1: Components

### Conductor Connection

Active: A  
Neutral: N  
Earth: E  $\perp$




Figure 2: Connections on Pin Housing

This Installation Guide was designed with great care and proper testing before publication to ensure the product works perfectly with TriCab flexible cables. TriCab is not liable for any errors, omissions, damages etc. due to improper use of this product, included but not limited to improper installation deviating from this Guide, safety and warning rules violation, using unsuitable cable other than TriCab flexible cable. TriCab reserves the right to modify this Installation Guide at any time without prior notice.

# J10

## Single-Phase Extension Socket Flat Pin Installation Guide

1. Select the suitable **J10 Straight Socket** by verifying the information given in Table 1 with the laser marking on the socket body. Unscrew the **Assembly Screws** and the **Lock Nut**. Mark the stripping length of the cable as shown in Figure 3 below.
2. Carefully cut and strip the outer layers of the cable (sheathing, insulation, fleece tape). Be very careful not to nick or cut any strands of the conductor. Adjust the stripping tool so that it cuts close to the conductor but leaves a small amount of insulation to tear away by hand. This will help protect the fine wires during the stripping process.
3. Insert the **Lock Nut**, **Cable Seal** and **Body** through the cable. Loosen the screw on the **Cord Clamp** connected to the **Pin Housing** and pass the insulated cores through it. Make sure that the outer sheathing of the cable is in the clamping position.
4. Loosen the **Terminal Screws** on the sides of the **Pin Housing**. Insert the conductors into the correct connection terminals as shown in Figure 2 and tighten the **Terminal Screws** to make a secure connection between the conductors and terminals.
5. Tighten the screw on the **Cord Clamp** to securely hold the outer sheathing of the cable. Adjust the components so that the body connects to the **Pin Housing**.
6. Place the **Sleeve** with the **Lock Ring** on the **Pin Housing**. Use the **Assembly Screws** to fix the **Sleeve**, **Pin Housing** and **Body** together.
7. Slide the **Cable Seal** up to the **Body** and screw the **Lock Nut** securely to complete the seal.




Figure 3: Cable Stripping Lengths

Table 1: Socket Specifications

Product Code	No. Sockets	Rating	Voltage	No. Phase
		A	V	
J10-AAXX/3P10	3 Flat Pins	10	250	1
J10-AAXX/3P15	3 Flat Pins	15	250	1

This Installation Guide was designed with great care and proper testing before publication to ensure the product works perfectly with TriCab flexible cables. TriCab is not liable for any errors, omissions, damages etc. due to improper use of this product, included but not limited to improper installation deviating from this Guide, safety and warning rules violation, using unsuitable cable other than TriCab flexible cable. TriCab reserves the right to modify this Installation Guide at any time without prior notice.